

Guarantee


Nightsearcher products have been carefully tested and inspected before shipment and are guaranteed to be free from defective materials and workmanship for a period of 12 months from the date of purchase, provided that the enclosed instructions have been followed.

Should you experience problems with your Nightsearcher product, please return the complete item including charger to your purchase stockist or contact Nightsearcher Ltd, at the address below.

If upon inspection it is found that the fault occurring is due to defective materials or workmanship repairs will be carried out free of charge. This guarantee does not apply to normal wear and tear, nor does it cover any damage caused by misuse, careless or unsafe handling, alterations, accidents, or repairs attempted or made by any personnel without prior approval from Nightsearcher Ltd. Bulbs are a consumable and are not covered by this guarantee. Your Nightsearcher guarantee is not effective unless you can produce a dated receipt of purchase.

Please note that this guarantee does not affect your statutory rights.

Safe disposal of waste electrical products, batteries and bulbs



If at any time in the future you should need to dispose of this product or any part of this product: Please note that waste electrical products, batteries and bulbs should not be disposed of with household waste. Please recycle where facilities exist, please check with your local authority for recycling advice.

 **NIGHTSEARCHER**

NS 750

PORTABLE RECHARGEABLE SEARCHLIGHT



USER INSTRUCTION MANUAL

NIGHTSEARCHER LIMITED

Unit 4 Applied House, Fitzherbert Spur, Farlington
Portsmouth, Hampshire, PO6 1TT, U.K.
Tel. +44 (0) 23 9238 9774 / Fax. +44 (0) 23 9238 9788
www.nightsearcher.co.uk

Your NIGHTSEARCHER NS750 rechargeable lamp has been designed to provide you with excellent performance for many years.

Important: Please read these instructions carefully to ensure the safe and effective use of this product.

CHARGING INSTRUCTIONS

To recharge simply connect the Jackplug into the Nightsearcher 750 and plug the charger into the mains. The LED light will come on red to show the lamp is charging and it will turn green to show when fully charged. Recharging time is approximately 12 hours if completely discharged or pro rata if not. The Nightsearcher 750 can be left on charge permanently without risk of damage to the battery.

WARNING

Please bear in mind that this is high-powered professional lamp, which generates considerable heat if left switched on in a confined space.

Store in a safe place and away from children.

Always recharge after use. Never leave the lamp in a discharged state. To do so could damage the battery and could result in the battery needing to be replaced. Do not switch the lamp on whilst charging or for the first five minutes afterwards as the charging voltage is higher and is likely to blow the bulb or reduce its life. Please ensure you use the correct replacement 12v x 10w Halogen bulb and 12v x 50w Xenon bulb, available from your local stockist .

The charging unit is CE Rated and should only be used indoors.

HELPFUL HINTS

TO CHANGE THE BATTERY: Undo the two screws on the lid and remove the two plastic nuts holding the PCB in place and remove. Remove the battery and replace with new battery. Refit in reverse order as taken apart ensuring correct connection to battery, i.e. RED to POSITIVE, BLACK to NEGATIVE.

TO CHANGE BULB: Unscrew the four screws on the lightfront's rim to gain access to the bulbholders. Undo the locking screw on the outer bulbholder and pull out the inner part of the bulbholder. The bulb itself will pull directly out of the holder. Care must be taken not to touch the Halogen bulb with bare hands as this will impair the performance and life of the bulb. Refit new bulb and fit into holder. You can now focus the light to desired beam by moving the lamp holder further in or out before doing up the locking screw. Refit the lightfront in the reverse order as taken apart.

REPLACEMENT PARTS

Should you require replacement parts for your lamp, it is essential that only the correct spares are purchased from your stockist.

	<u>PART NUMBER</u>
12v Mains Charger for NS 750	CH12V750
12v Incar Charger Lead	CH12V750INCAR
12v x 7a/h Battery	BA12X7
12v x 10w Halogen Bulb	BU12X10
12v x 50w Xenon Bulb	BU12X50
Replacement Lens for NS 750	SP750SPOT
Replacement Reflector for NS 750	SPP750REF
Replacement PCB for NS 750	SP750PCB

Details of various other parts are available from your stockist