

## WARRANTY

Your Nightsearcher Endurance Hand Lamp has a 12 month warranty from the date of purchase on all parts excluding bulbs, provided that the enclosed instructions have been followed. Nightsearcher Limited shall have no liability under the warranty in respect of defects arising from fair wear and tear, wilful damage, neglect or alteration or repair to the goods without approval from Nightsearcher Limited.

If you should experience problems with your Nightsearcher Endurance Hand Lamp, please return your lamp complete with charger either to your local stockist or to us at:



Unit 4 Applied House,  
Fitzherbert Spur, Farlington,  
Portsmouth PO6 1TT, U.K.  
<http://www.nightsearcher.co.uk>

# NIGHTSEARCHER

# ENDURANCE

## RECHARGEABLE HANDLAMP

User Instructions

## OPERATION INSTRUCTIONS FOR NIGHTSEARCHER ENDURANCE RECHARGEABLE HANDLAMP

Please read this instruction sheet carefully and follow the advice given before using your Rechargeable Lamp. This will ensure that your lamp will function properly over a long period of time.

1. You should immediately charge your Lamp for about 24 hours before use. This will completely charge and recondition the battery for optimum performance. Charge adaptor and Lamp may, for an indefinite time, be left connected to the mains supply beyond the suggested 24 hours initial charge period. Power consumption is negligible, elaborate charge electronics will avoid battery damage.
2. After extended use of your Lamp the red signal lamp (LED) will start blinking—this is to remind you that the battery is running low in power and that recharging is necessary. You are now left with several minutes of light output, after this period blinking will stop and the internal electronics will cut off power. This is to ensure that the rechargeable battery is not subjected to gradual damage by repeated deep discharge or by unintentional activation of the digital switch. (e.g. carelessly placing the Lamp into a tightly packed sports bag, etc.)
3. When your Lamp is charging, the yellow signal lamp (LED) will light as long as the battery accepts charging current. Towards the end of the charging period the yellow signal lamp will gradually fade into a darker state until it is off. This would indicate that the bulk of the charge has been taken up by the battery and that your Lamp is ready for use. The Lamp may remain on charge indefinitely, with out risking damage to the battery.

## REPLACING THE BULB

- Switch off your Hand Lamp
- Unscrew the Lamp Head Anticlockwise
- Carefully pull the Lamp Holder (with 3 spring prongs) off the reflector
- Remove the old Bulb and replace it with the new Krypton Bulb (BU6VEND)
- Insert the Lamp Holder into the reflector opening
- Align the 3 prongs with the grooves of the reflector, cautiously push until the prongs engage well
- Screw the Lamp Head Back on, mind that the lead wires do not entangle with the Lamp Holder.

### WARNING

Always recharge after use, never leave the Lamp in a discharged state. To do so could damage the battery and could result in the battery needing to be replaced.

Please ensure that you use the correct replacement 6-volt Krypton bulb (BU6VEND), available from you local stockist or direct from ourselves.

The charging unit is CE Rated and should only be used indoors.

## SPARES AND ACCESSORIES

The following spares and accessories are available from your local stockist or direct from us:

### DESCRIPTION

6v Krypton Bulb  
6v 4a/h Battery  
Mains Charger for Endurance  
In Car Charger for Endurance  
Case\Switch\Wireset for Endurance  
Lightfront for Endurance

### NIGHTSEARCHER PRODUCT CODE

BU6VEND  
BA6X4  
CH12VEND  
CH12VENDINCAR  
SPENDCASE  
SPENDLF