

• **NightSearcher Guarantee**

Nightsearcher products have been carefully tested and inspected before shipment and are guaranteed to be free from defective materials and workmanship for a period of 12 months from the date of purchase, provided that the enclosed instructions have been followed.

Should you experience problems with your product, please return the complete item to your place of purchase or contact NightSearcher (details printed on manual).

If upon inspection it is found that the fault occurring is due to defective materials or workmanship, repairs will be carried out free of charge. This guarantee does not apply to normal wear and tear, nor does it cover any damage caused by misuse, careless or unsafe handling, alterations, accidents, or repairs attempted by any personnel without prior approval from Nightsearcher.

Your Nightsearcher guarantee is not effective unless you can produce a dated receipt of purchase. This guarantee does not affect your statutory rights.

 **NIGHTSEARCHER**

TRiO

Rechargeable LED Hand-Lamp

 **NIGHTSEARCHER**

Unit 4 Applied House,
Fitzherbert Spur, Farlington,
Portsmouth, PO6 1TT, U.K.

T: +44 (0)23 9238 9774

F: +44 (0)23 9238 9788

E: sales@nightsearcher.co.uk

W: www.nightsearcher.co.uk



USER MANUAL

CE

Before using your NightSearcher TRiO LED Hand-Lamp, please read this user manual, it contains important safety information and the operating instructions.

• **Technical Specification:**

Light Source	3x 0.5W LED
Light Output	75 lumens
Battery	Rechargeable 6V 4A/h
Running Time	13 hours
Charge Time	15 hours approx
Product Size (mm)	L189 x W112 x H128.5
Weight (kg)	1.00
Part No.	NSTRIO

• **Features:**

- Long running rechargeable LED hand-lamp, operating for up to 13 hours
- LED indicator for battery charging status (Red = charging, Green = fully charged)
- Emergency function = Automatically illuminates in the event of a power cut
- Automatic shut down when the battery is fully charged (to avoid over charging)
- RoHS and CE compliant
- Robust polypropylene casing
- **Pack includes:** ABS wall mounting bracket, detachable shoulder strap, mains and vehicle charger.

• **Battery Charging**

1. You should immediately charge your lamp for 24 hours before use. This will completely charge and recondition the battery for optimum performance. Charge adaptor and lamp may, for an indefinite time, be left connected to the mains supply beyond the suggested 24 hours initial charge period. Power consumption is negligible, elaborate charge electronics will avoid battery damage.
2. After extended use of your lamp it will automatically switch off, this is to remind you that the battery is running low in power and that recharging is necessary. You are now left with several minutes of light output, after this period, the lamp is to be switched off completely and fully recharged. This is to ensure that the rechargeable battery is not subjected to gradual damage by repeated deep

discharge or by unintentional activation of the digital switch. (e.g. carelessly placing the lamp into a tightly packed sports bag, etc.)

3. When your lamp is charging, the red indication light (LED) will illuminate as long as the battery accepts the charging current. Towards the end of the charging period the red indication light will switch to green. This would indicate that the bulk of the charge has been taken up by the battery and that your lamp is ready for use. The lamp may remain on charge indefinitely, with out risking damage to the batter.

• **Emergency Function**

Turn the lamp to ON mode, the red LED directly below the on / off switch will illuminate. Position in the lamp in the mounting bracket and connect the charging adaptor. Connect the charging adaptor to the AC power supply. The lamp will switch off and the red LED will remain lit. During the charging process, if the electricity supply is cut off or disconnected, the lamp will automatically illuminate.

WARNING

Never leave the lamp in a discharged state, always recharge after use, and recharge every 3 months. *Failing to do so will damage the battery and could result in the battery needing to be replaced.*

The charging unit is CE rated and should only be used indoors.

• **LED Assembly Replacement**

The Light Emitting Diodes (LED) can last up to 100,000 hours and seldom need to be replaced. If there is any malfunction of LEDs, please contact NightSearcher or an authorised distributor.

• **Safe disposal of waste electrical products, batteries and bulbs**



If needing to dispose of this product or parts of this product: Please note that waste electrical products, batteries and bulbs should not be disposed of with household waste. Recycle where facilities exist, please check with your local authority for recycling advice.