

 **NIGHTSEARCHER**

GUNLIGHT KIT

RECHARGEABLE KIT



USER MANUAL

NIGHTSEARCHER LTD
Unit 4 Applied House
Fitzherbert Spur, Farlington
Portsmouth, Hampshire, PO6 1TT
United Kingdom

www.nightsearcher.co.uk



If at any time in the future you should need to dispose of this product or any part of this product: Please note that waste electrical products, batteries and bulbs should not be disposed of with household waste. Please recycle where facilities exist, please check with your local authority for recycling advice.

CE

1/ RECHARGING YOUR NIGHTSEARCHER LAMP:

Your Nightsearcher Power Pack will give you approximately 1-2 hours of light from a single charge. The SEALED LEAD ACID battery used can be recharged at any state of discharge. We recommend you recharge your battery after any use.

It is important to remember never to allow the batteries to remain in a completely discharged state for more than two days. To do so will damage the battery permanently. Once the battery is recharged it will store its charge for a long period. If the battery has not been in use for a while it is best to recharge it completely before using it, or every three months when not in use. If your battery is properly used it can give up to 1,000 recharges.

The recharging time of your battery is 12 hours if completely discharged or approximately 6 hours if in use for only 1 hour.

To prolong the life of your bulb, allow the battery to settle for 10 minutes after recharging before turning the lamp on. If necessary replacement bulbs and batteries are available from your local stockist or direct from ourselves.

2/ CHANGING THE BULB:

Put a point object (or a ball point pen) into one of the two holes on the gunlight, whilst holding the gunlight in the other hand. Twist them anti clockwise to remove the locking ring. Underneath the locking ring is an O ring and the glass lens. Remove these and pull the bulb out. Push in the new bulb, and reverse the process for removing the bulb.

3/ WARNING:

You must ensure that only the correct parts are used in your Nightsearcher Gunlight.

4/ SPARES AND ACCESSORIES:

The following spares and accessories are available from your local stockist or direct from us:

PART DESCRIPTION	PRODUCT CODE
12V 50W Bulb	BU12X50
12V 7a/h Sealed Lead Acid Battery	BA12X7
12V Mains Charger	CH12VGUN
12V Incar Charger	CH12VGUNINCAR
Reflector for Gunlight	SP400REF
Clear Lens for Gunlight	SP400LENS
Wireset for Gunlight	SP400WIRESET

OPTIONAL ACCESSORIES	PRODUCT CODE
12V 100W Bulb	BU12X100
Red Filter for Gunlight	SP400R
Blue Filter for Gunlight	SP400B
Amber Filter for Gunlight	SP400A

5/ WARRANTY:

Nightsearcher products have been carefully tested and inspected before shipment and are guaranteed to be free from defective materials and workmanship for a period of 12 months from the date of purchase, provided that the enclosed instructions have been followed.

Should you experience problems with your Nightsearcher product, please return the complete item including charger to your purchase stockist or contact Nightsearcher Ltd, at the address below.

If upon inspection it is found that the fault occurring is due to defective materials or workmanship repairs will be carried out free of charge. This guarantee does not apply to normal wear and tear, nor does it cover any damage caused by misuse, careless or unsafe handling, alterations, accidents, or repairs attempted or made by any personnel without prior approval from Nightsearcher Ltd. Bulbs are a consumable and are not covered by this guarantee.

Your Nightsearcher guarantee is not effective unless you can produce a dated receipt or invoice to verify your proof of purchase within the 12 month period.

Please note that this guarantee does not effect your statutory rights